ISSUED 2018/05/21

Main PWB 1 / 2

Applicable model
KMM-125
KMM-105GY
KMM-105AY
KMM-105RY
KMM-105M



Model List		
Model No.	Model Name.	Unit No.
YJ1-142E-00	KMM-205E	XJ1-248E-01
YJ1-142E-01	KMM-105RYE2	XJ1-248E-01
YJ1-142E-02	KMM-105GYE2	XJ1-248E-01
YJ1-142E-03	KMM-105AYE2	XJ1-248E-01
YJ1-142M-01	KMM-105MM2	XJ1-248M-01
YJ1-142M-02	KMM-105M	XJ1-248M-02
YJ1-143E-00	KMM-125E	XJ1-248E-02

MODEL NAME:Refer Model List on page 1/2

CAUTION:
FOR CONTINUED SAFETY REPLACE SAFETY CRITICAL COMPONENTS ONLY WITH MANUFACTURERS RECOMMENDED PARTS INDICATES SAFETY CRITICAL COMPONENTS.
⚠ TO REDUCE RISK OF ELECTRIC SHOCK, LEAKAGE CURRENT APPLIANCES RETURNED TO THE CUSTOMER.
EXPOSED PARTS ARE ACCEPTABLY INSULATED FROM SUPPLY CIRCUIT.

KENWOOD
KMM-205 etc.
JVCKENWOOD Corporation

ISSUED
2018/05/21

DIFFERENCE TABLE

Symbol Number	KMM-205	KMM-105AY KMM-105GY KMM-105RY	KMM-125	KMM-105M	M-02 KMM-105M
SW1/SW2 BEAT NOISE C/M					
*C9089	-	-	-	-	CK73HXR1A105K_9
*C9090	-	-	-	-	CK73HXR1A105K_9
*C9091	-	-	-	-	CK73HXR1A105K_9
*C9092	-	-	-	-	CK73EXR1E106K_9
PREOUT JACK SETTING					
*J321	E6D-0014-00	E6D-0014-00	E6D-0015-00	E6D-0016-00	E6D-0014-00
*C261	CK73EXR1C475K_9	CK73EXR1C475K_9	CK73EXR1C475K_9	-	CK73EXR1C475K_9
*C321	-	-	CK73EXR1C475K_9	CK73EXR1C475K_9	-
*C331	-	-	CK73EXR1C475K_9	CK73EXR1C475K_9	-
*C341	-	-	-	CK73EXR1C475K_9	-
*C351	-	-	-	CK73EXR1C475K_9	-
*Q260	KRC410E-P_9	KRC410E-P_9	KRC410E-P_9	-	KRC410E-P_9
*Q320	-	-	KRC410E-P_9	KRC410E-P_9	-
*Q330	-	-	KRC410E-P_9	KRC410E-P_9	-
*Q340	-	-	-	KRC410E-P_9	-
*Q350	-	-	-	KRC410E-P_9	-
*R253	-	-	-	RK73GB2A000J_9	-
*R260	RK73HB1J181J_9	RK73HB1J181J_9	RK73HB1J181J_9	-	RK73HB1J181J_9
*R261	RK73HB1J223J_9	RK73HB1J223J_9	RK73HB1J223J_9	-	RK73HB1J223J_9
*R262	RK73HB1J331J_9	RK73HB1J331J_9	RK73HB1J331J_9	-	RK73HB1J331J_9
*R320	-	-	RK73HB1J181J_9	RK73HB1J181J_9	-
*R321	-	-	RK73HB1J223J_9	RK73HB1J223J_9	-
*R323	-	-	RK73HB1J331J_9	RK73HB1J331J_9	-
*R330	-	-	RK73HB1J181J_9	RK73HB1J181J_9	-
*R331	-	-	RK73HB1J223J_9	RK73HB1J223J_9	-
*R333	-	-	RK73HB1J331J_9	RK73HB1J331J_9	-
*R340	-	-	-	RK73HB1J181J_9	-
*R341	-	-	-	RK73HB1J223J_9	-
*R343	-	-	-	RK73HB1J331J_9	-
*R350	-	-	-	RK73HB1J181J_9	-
*R351	-	-	-	RK73HB1J223J_9	-
*R353	-	-	-	RK73HB1J331J_9	-
OE/REMOTE SETTING					
*R402	-	-	-	RK73HB1J225J_9	RK73HB1J225J_9
*R403	RK73GB2A473J_9	RK73GB2A473J_9	RK73GB2A473J_9	-	-
IPOD/IPHONE					
*IC411	MFI337S3959O1_9	-	-	-	-
*C410	CK73HXR1A104K_9	-	-	-	-
*R410	RK73HB1J101J_9	-	-	-	-
*R411	RK73HB1J101J_9	-	-	-	-
*R412	RK73HB1J472J_9	-	-	-	-
*R413	RK73HB1J472J_9	-	-	-	-
*R414	RK73GB2A472J_9	-	-	-	-
STAGE SETTING					
*R732	RK73HB1J394J_9	-	-	RK73HB1J334J_9	-
*R733	RK73GB2A823J_9	RK73GB2A474J_9	RK73GB2A474J_9	RK73GB2A154J_9	RK73GB2A474J_9
*R734	RK73HB1J394J_9	RK73HB1J394J_9	RK73HB1J394J_9	RK73HB1J394J_9	RK73HB1J334J_9
*R735	RK73HB1J823J_9	RK73HB1J823J_9	RK73HB1J823J_9	RK73HB1J823J_9	RK73HB1J154J_9
HORN NOISE C/M					
*C9003	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
*C9004	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
*C9005	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
*C9006	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
*C9007	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
*C9008	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
*C9009	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
*C9010	-	-	-	CK73HXR1H471K_9	CK73HXR1H471K_9
POWERCORD ASSY	E3A-0320-00	E3A-0320-00	E3A-0320-00	E3A-0324-00	E3A-0324-00

XJ1-243 Stage	E-00 Voltage	E-01 Voltage	E-02 Voltage	M-01 Voltage	M-02 Voltage
PIN 54 STAGE 2	0.57V	0V	0V	1.03V	0V
PIN 55 STAGE 1	0.57V	0.57V	0.57V	0.57V	1.03V

Applicable model
KMM-125
KMM-105GY
KMM-105AY
KMM-105RY
KMM-105M

Main PWB 2 / 2

CONFIDENTIAL

MODEL NAME: Refer Model List on sheet 1/2

CAUTION:
FOR CONTINUED SAFETY REPLACE SAFETY CRITICAL COMPONENTS ONLY WITH MANUFACTURERS RECOMMENDED PARTS INDICATES SAFETY CRITICAL COMPONENTS.
⚠ TO REDUCE RISK OF ELECTRIC SHOCK, LEAKAGE CURRENT APPLIANCE IS RETURNED TO THE CUSTOMER.
(EXPOSED PARTS ARE ACCEPTABLY INSULATED FROM SUPPLY CIRCUIT)

KENWOOD
KMM-205 etc.
JVCKENWOOD Corporation